



SAM-RFBA18

1x8 Bi-directional amplified splitter, 1GHz, SCTE compliant, includes terminator caps and external DC power adapter



SAM-RFBA38

3x8 Bi-directional amplified splitter, 1GHz, SCTE compliant, includes terminator caps and external DC power adapter

Product Description

The 1x8 and 3x8 Bi-directional RF Splitters provide better signal quality on all the home's TVs and save space in the enclosure. Plug the incoming signals from the CATV, satellite (after set-top box), or antenna into the input. Auxiliary ports 2 and 3 on the SAM-RFBA38 can also be used for other modulated signals from DVD/VCRs or security cameras. Then plug the power adapter in and you're ready to start enjoying better video quality throughout the home.

Specifications

Frequency Range	-----	5-42/54-1000MHz
Isolation	-----	20-30dB
RFI Shielding	-----	110dB
Input & Output Connectors	-----	SCTE 02 2006 compliant F-Female Machined brass, Nickel plated
Power Requirement	-----	300mA, 12V, with 2.5mm adapter input - 60" corded adapter, LED indicator
Gain	-----	4.5dB forward gain per port/0dB reverse gain
Operating Temperature	-----	-40 to 60° C (-40 to 140° F)
Dimensions	-----	3.5"H x 6.5"W x 3"D

Features

- SCTE compliant "F" ports
- Auxiliary ports 2 and 3 can also be used to pass signal from DVD/VCRs or security cameras
- 75 Ohm terminators included for unused ports
- DC power adapter included

